



Spy Security Systems

FS148B WIRELESS OUTDOOR SIREN & STROBE

The FS148B Wireless External Siren with Strobe can combine with security console by wireless control for increasing the panic effect the Sirens installed in different location can also be triggered simultaneously upon Main Console in the house being activated.

- Wireless plug.
 - Operating modes: Disarmed, Armed and 24 hours Panic.
 - Adopts narrow band AM superior super heterodyne receiver technology.
 - LED light indicators for AC Power Failure or tamper switch, Armed Status and Signal Received.
 - 4 different alarm sounds so the user knows the type of emergency upon hearing the siren.
 - Built-in 110-dB siren and Strobe.
 - The alarm duration can be setting to 1 or 3 minutes easily by switch.
 - Built-in rechargeable back-up battery.
 - Built-in strobe light to display alarm mode, still disarmed to off.
 - Built-in Tamper Switch and Power Failure Detector function.
-
- Power Source: DC 12-16 V 1A by AC adapter
 - Stand-By Current: 15 mA (Max.), Working Current: 600 mA (Max.)
 - Broadcast Range: 100 M in a free space, indoors about 30 M.
 - Working Frequency: 433.92 or 869.25 MHz.
 - Back-up Battery: 9.6V / 1.2 Hhr rechargeable.
 - Battery Back-Up Time: 24 Hrs. (Min.)
 - Working Temperature Range: -10 deg C to 60 deg C.

